


19*17cm

OPERATION INSTRUCTION



一. Function:

1. Weekday/Year(2000~2099), Date,Hour,Minute,Second display;
2. A group daily Alarm and Hourly chime function;
3. Dual-time display
4. Timer;
5. Chronographic.
6. EL backlight
7. 3 Hands QZ Movement

二. Operation instruction:

1. In any mode, Push "Light" key to activate EL backlight;
2. In time mode,Push "Mode" key to shift modes with frequencies: Time--Alarm--Chrono--Dual Time--Timer
3. In time mode, Hold "RESET" into time setting mode and "Second" is blinking ,Push "START" to adjust the value,Push "MODE" to shift with frequencies as below:Second- Hour - Minute -Year (2000~2099)-Month-Date. Push "RESET" to confirm setting and quit .
In Time model, push "START" to shift 12H/24H display
4. In time mode, Push "Mode" into alarm mode, push "RESET" key to turn on/off the alarm and hourly chime function;
5. In Alarm Mode, Hold "RESET" key into alarm setting mode and "Hour" is blinking, Push "START" to adjust the value, Push "MODE" to shift Hour and Minute, Push "RESET" to

confirm set,push "MODE" return time display mode;

In time mode, Push "Mode" twice into Chrono mode,Max measurement: 23H59M59.99Sec;Push "START" to start, push "START" again to pause,push "RESET" to reset

During Chrono, Push "RESET" into new Channel Chrono "LO1",push "START" to start to Chrono "LO1", push "RESET" into new Channel Chrono "LO2", same way up to max 12 Channels.

During Multi channels running, push "START" to pause , push "RESET" to display LO1 result, push "RESET" again to display LO2 result, same way up to max 12 Channels.

During pause, Hold "RESET" to rest all the channels.

6. In time mode, Push "Mode" Three times into Dual-Time mode, Dual-Time mode, push "RESET" key into Dual time setting mode and "Hour" is blinking, Push "START" to adjust the value, Push "MODE" to shift Hour and Minute, Push "RESET" to confirm set,push "MODE" return time display mode;
7. In time mode, Push "Mode" four times into count-down timer mode, in timer mode, push "RESET" key into timer setting mode and "second" is blinking, Push "MODE" to shift Hour , Minute and second, Push "START" to adjust the value, Push "RESET" to confirm set,push "START" to start count-down;
push "START" key to turn on/off Count-down timer mark;